



CRICKET

POLARITY/ CONTINUITY TEST SET

GALAXY AUDIO

CRICKET CPTS

Polarity, should it become reversed, can play havoc with a sound system. If two sources are emitting the same electrical or acoustic tone (frequency), and one of those sources is in a state of inverted polarity, those tones, when combined at a given point, will cancel each other. While cancellation does not always indicate a complete loss of all sound, it does result in diminished sound quality. Unlike phase, polarity, at all distances and times, is either in or out. It's absolute. Galaxy Audio's battery powered Cricket Polarity/Continuity Test Set makes it easy to determine whether every component in an audio system from patch bay to console to speakers is in or out of polarity. The Cricket tests balanced and unbalanced cables of up to 2,000 feet in length. It will drive a "snake" (even one with transformers), and indicate which of a microphone's XLR connector pins is hot. The Cricket can also plug directly into a speaker cabinet and drive the components. A glance at the Cricket's red and green LED's can save hours of troubleshooting. No wonder it's an indispensable tool for sound system owners, operators, installers and sound rental companies.





CRICKET

GALAXY AUDIO

POLARITY/ CONTINUITY TEST SET

In even the simplest sound systems there are all sorts of ways for polarity to become reversed; the more complex the system, the greater the potential for problems. The Cricket can test the polarity of wireless microphones, mixers, effects devices, amps, cables, and speakers.

SPECIFICATIONS

Cricket Send Pulse Generator

Pulse Waveform Polarity: positive-going balanced line output pulse, switch selectable for hi or low level balanced signal with positive pressure produced at the tip of 1/4-inch jack and pin #2 of XLR jack.

Speaker Output Pulse: Accepts 2 ohm (or greater) load with positive pressure produced at the tip of a 1/4-inch speaker jack and positive terminal of an internal speaker.

Dimensions: 3.33"W x 1.75"H x 5.25"L

Weight (with battery): 1.10 lbs. (.5 kg.)

Battery: 9 volt, alkaline only (battery included)



Cricket Recieve Pulse Detector

LED Indicators:

Green: indicates positive-going pulse polarity with power switch in "ON" position and battery status with power switch in "BAT" position.

Red: indicates negative-going pulse polarity.

Detection inputs: one 1/4-inch, balanced; one XLR, balanced.

Mic Sensitivity: -64 dB, +3 dB

Weight (with battery): 1.02 lbs. (.46 kg.)

Battery: 9 volt, alkaline only (battery included)

Switches: Internal microphone for testing speaker output.

Polarity/Continuity Test: Female XLR pin 2,3,1 continuity; 1/4-inch jacks: tip, ring, sleeve continuity.

Test set shipping weight: 3 lbs. (1.36 kg.)



Convenient operation charts located on the under side of each unit.

Blister packaged for retail sale.



Specifications subject to change without notice.

GALAXY AUDIO

MAKERS OF THE ORIGINAL HOT SPOT PERSONAL MONITOR

601 E. Pawnee Wichita, KS 67211 316.263.2852 FAX 316.263.0642 www.galaxyaudio.com

Distributed outside the United States by E and E Exports, Inc. 2815 Junipero Ave. Suite 101 Signal Hill, CA 92614
562.988.3447 FAX 562.989.3037

Distributed in Canada by Cable Tek/JP Cabletek Electronics, Ltd. 1638 Kebet Way Building 100 Port Coquitlam, BC V3C 5W9
604.942.1001 FAX 604.942.1010